

Traktor Pro 2.5 setup 'faderfox DS3 V02.tsi'

- Sample deck mode -

Slot 1/2/3/4	Volume of selected sample slot Push to mute / unmute the sample Push to show value in display	Filter control of selected sample slot Push to enable / disable the filter Push to show value in display	Sample length of selected slot Push to switch between loop mode / one shot mode Push to show value in display	
Volume	Volume of sample slot 1 Push to mute / unmute the sample Push to show value in display	Volume of sample slot 2 Push to mute / unmute the sample Push to show value in display	Volume of sample slot 3 Push to mute / unmute the sample Push to show value in display	Volume of sample slot 4 Push to mute / unmute the sample Push to show value in display
Filter	Filter control of sample slot 1 Push to enable / disable the filter Push to show value in display	Filter control of sample slot 2 Push to enable / disable the filter Push to show value in display	Filter control of sample slot 3 Push to enable / disable the filter Push to show value in display	Filter control of sample slot 4 Push to enable / disable the filter Push to show value in display

Loop recorder Play
Loop recorder Delete

Loop recorder Dry/Wet
Push to copy to sample slot *

Loop recorder Size

Loop recorder Record
Loop recorder Undo/Redo

Select functions of the four multifunctional encoders above (green led of selected group blinks) shift + group 1-4 key toggles between Slot (blinks) & FX group (lit)

Deck select
hold down and press sample key 1-4 to copy a loop from deck into sample slot

Toggle deck mode
led is lit = track deck mode
led blinks = sample deck mode

Press both Deck C & D buttons to get traktors monitor state (led refresh)

Retrigger sample 1-4
led is lit for loaded one shot sample
led blinks while sample plays

Sample cue of slot 1-4

Synchronize the deck to the current tempo source
Define the deck as sync master

Play / pause (play all samples in the deck)
Cue (monitor)

Select previous favorite
Select favorite 'Track collection'

Browse thru track list
Push to load selected remix set *
Browse thru tree
Push to expand/collapse tree

Toggle browser view
Select next layout

Select next favorite
Select favorite 'All samples'

FX assign to the currently selected deck
FX enable for sample slot 1-4

Play / stop sample 1-4
led is lit for loaded loop sample
led blinks while sample plays
Delete sample 1-4

Cue pause (Cup)
Bend forward

Cue play
Bend backward

* To copy/load in desired sample slot please hold down loop recorder or browser encoders and press the corresponding sample key 1-4

! Hold shift button for 2nd functions written on yellow (light gray) background